

Data-Driven Room Acoustic Modeling Via Differentiable Feedback Delay Networks With Learnable Delay Lines

Alessandro Ilic Mezza^{1*}, Riccardo Giampiccolo¹, Enzo De Sena²,
Alberto Bernardini¹

^{1*}Dipartimento di Elettronica, Informazione e Bioingegneria, Politecnico di Milano,
Piazza Leonardo da Vinci, 32, Milan, 20133, Italy.

²Institute of Sound Recording, University of Surrey, Stag Hill, University Campus,
Guildford, GU27XH, UK.

*Corresponding author(s). E-mail(s): alessandroilic.mezza@polimi.it;
Contributing authors: riccardo.giampiccolo@polimi.it; e.desena@surrey.ac.uk;
alberto.bernardini@polimi.it;

Abstract

Over the past few decades, extensive research has been devoted to the design of artificial reverberation algorithms aimed at emulating the room acoustics of physical environments. Despite significant advancements, automatic parameter tuning of delay-network models remains an open challenge. We introduce a novel method for finding the parameters of a Feedback Delay Network (FDN) such that its output renders target attributes of a measured room impulse response. The proposed approach involves the implementation of a differentiable FDN with trainable delay lines, which, for the first time, allows us to simultaneously learn each and every delay-network parameter via backpropagation. The iterative optimization process seeks to minimize a perceptually-motivated time-domain loss function incorporating differentiable terms accounting for energy decay and echo density. Through experimental validation, we show that the proposed method yields time-invariant frequency-independent FDNs capable of closely matching the desired acoustical characteristics, and outperforms existing methods based on genetic algorithms and analytical FDN design.

Keywords: Automatic differentiation, differentiable feedback delay networks, room acoustics.

1 Introduction

Room acoustic synthesis involves simulating the acoustic response of an environment, a task that finds application in a variety of fields, e.g. in music production, to artistically enhance sound recordings; in architectural acoustics, to improve the acoustics of performance spaces; or in VR/AR/-computer games, to enhance listeners' sense of realism [1], immersion [2], and externalization [3].

Room acoustic models can be broadly classified in physical models, convolution models, and delay-network models [4]. Physical ones can be further divided in wave-based models, which provide high physical accuracy but at the cost of significant computational complexity, and geometrical-based ones, which make the simplifying approximation that sound travels like rays. Convolution models involve a set of stored room

impulse responses (RIRs) and are therefore capable of replicating the true response of a real room [4]. Convolution is, however, an operation that despite recent advances [5] still carries a computational load that makes it ill-suited in certain real-time applications.

Delay-network models consist of recursively connected networks of delay lines and have a significantly lower computational cost than convolution. Rather than modeling the physical response of a specific room, delay-network models only aim to replicate certain perceptual aspects of room acoustics. These models have a long history, which can be traced back to the Schroeder reverberator [6]. Since then, a number of designs have been proposed, including feedback delay networks (FDNs) [7–9], scattering delay networks (SDNs) [10], and waveguide networks (WGNs) [11].

The parameters of delay-network models are typically designed to obtain certain desired acoustical characteristics, e.g., a target reverberation time. An alternative design paradigm is to fit the parameters such that the output is as close as possible to that of a measured RIR, hence combining the accuracy of convolution models with the low computational complexity of delay-network models. Several methods following this alternative design paradigm have been recently proposed for the case of FDNs, for instance using gradient-free methods [12–16] and gradient-based machine learning techniques [17, 18]. Existing approaches, however, involve a certain degree of human intervention and require heuristic-driven ad-hoc choices for several model parameters.

This paper proposes a new method for automatic FDN parameter tuning. The present work is rooted in a recent framework for the parameter estimation of lumped-element models [19] based on automatic differentiation [20], and its novelty is twofold. First, the cost function combines two objective measures of perceptual features, i.e., the energy decay curve (EDC) and a differentiable version of the normalized echo density profile (EDP) [21]. Second, the delay line lengths are optimized via backpropagation along with every other FDN parameter, thus allowing exploiting the flexibility of delay-network models to the fullest. We thus introduce a simple, robust, and fully automatic method for matching acoustic measurements at scale. The learned parameters can be




Fig. 1 Block diagram of a SISO FDN with $N = 3$.

then seamlessly plugged into off-the-shelf FDN software without further processing or mapping.

The paper is organized as follows. Section 2 introduces the background information on FDNs. Section 3 discusses the prior art on automatic FDN parameter tuning. Section 4 describes the proposed method, and Section 5 presents its evaluation. Section 6 concludes the manuscript.

2 Feedback Delay Networks

The block diagram of a single-input-single-output (SISO) FDN is shown in Figure 1. This system is characterized by [22]

$$\begin{aligned} y[n] &= \mathbf{c}^T \mathbf{s}[n] + du[n] \\ \mathbf{s}[n + \mathbf{m}] &= \mathbf{A} \mathbf{s}[n] + \mathbf{b}u[n], \end{aligned} \quad (1)$$

where $u[n]$ is the input signal, $y[n]$ is the output signal, $\mathbf{b} \in \mathbb{R}^N$ is a vector of input gains, $\mathbf{c} \in \mathbb{R}^N$ is a vector of output gains, $(\cdot)^T$ denotes the transpose operation, $\mathbf{A} \in \mathbb{R}^{N \times N}$ is the feedback matrix, $d \in \mathbb{R}$ is the scalar gain associated to the direct path, and $\mathbf{m} = [m_1, \dots, m_N]$ is a vector containing the length of the N delay lines expressed in samples. The vector $\mathbf{s}[n] \in \mathbb{R}^N$ denotes the output of the delay lines at time index n , and we use the following notation $\mathbf{s}[n + \mathbf{m}] = [s_1[n + m_1], \dots, s_N[n + m_N]]^T$ to indicate N parallel delay operations applied to $\mathbf{s}[n]$ of $m_1, \dots, m_N$ samples, respectively.

If $\mathbf{m} = [1, \dots, 1]$, then (1) corresponds to the measurement and state equations of a state-space model. In other words, an FDN corresponds to a generalized version of a state-space model with non-unit delays [22].

The standard approach to designing the FDN parameters involves choosing the feedback matrix,

delays, and input/output weights so as to obtain certain desired acoustic characteristics—usually a sufficient echo density and a pre-set reverberation time. The most important parameters are the ones associated to the recursive loop, i.e., $\mathbf{m}$ and $\mathbf{A}$, since they determine the energy decay behavior of the model, as well as its stability. The delays, $\mathbf{m}$, are typically chosen as co-prime of each other, so as to reduce the number of overlapping echoes and increase the echo density [23]. The design of the feedback matrix, $\mathbf{A}$, starts from a lossless prototype, usually an orthogonal matrix such as Hadamard or Householder matrix, which have been shown to ensure (critical) stability regardless of the delays, a property defined by Schlecht and Habets as *unilosslessness* [8]. Losses are then incorporated by multiplying the unilossless matrix by a diagonal matrix of scalars designed to achieve a pre-set reverberation time, T_{60} .

While it is possible to design feedback matrices as time varying and/or frequency dependent [7, 24], this paper focuses on the time-invariant and frequency-independent case. With this assumption, the stability of the system can be easily enforced throughout the training, thanks to the model reparameterization strategies discussed later in Section 4.

Moreover, such a model benefits from having a low computational complexity. From visual inspection of Figure 1, indeed, an FDN only requires $2N + 1$ multiplications, $2N$ additions and one vector-matrix multiplication per sample. The vector-matrix multiplication requires N^2 scalar multiplications and $N(N - 1)$ additions for the case of a generic feedback matrix (while it becomes $O(N)$ for a Householder matrix). Assuming equal cost of additions and multiplications, the overall computational complexity of an FDN amounts to $f_s (2N^2 + 3N + 1)$ floating-point operations per second (FLOPS), where f_s is the sampling rate. For $N = 6$ and $f_s = 44.1$ kHz, that corresponds to a computational complexity of 4 MFLOPS. For comparison, modeling a 0.5 seconds long RIR using an FIR filter (i.e., naive convolution) at the same sampling rate would carry a computation complexity of 1945 MFLOPS. In real-time applications one would normally use faster methods such as partitioned convolution [5] or overlap-add (FFT-based) convolution [25]. Under the same conditions and assuming a frame refresh rate of

50 Hz, overlap-add convolution carries a complexity of 207 MFLOPS [10], which is still nearly two orders of magnitude larger than an FDN.

3 Related Work

As mentioned earlier, automatic tuning of FDN parameters has been previously investigated by means of gradient-free methods, such as Bayesian optimization [12] and genetic algorithms [13–16], as well as gradient-based machine learning techniques [17, 18].

Some works are concerned with the automatic tuning of off-the-shelf reverberation plugins. In [26], Heise and colleagues investigate four gradient-free optimization strategies: simulated evolution [27], the Nelder-Mead simplex method [28], Nelder-Mead with brute-force parallelization, and particle swarm optimization [29]. More recently, [12] applies Bayesian optimization using a Gaussian process as a prior to iteratively acquire the control parameters of an external FDN plug-in that minimize the mean absolute error between the multiresolution mel-spectrogram of the target RIR convolved with a 3-second logarithmic sine sweep and that of the artificial reverberator output. The FDN control parameters include the delay line length, reverberation time, fade-in time, high/low cutoff, high/low Q, high/low gain, and dry-wet ratio.

Conversely, other studies assume to have white-box access to the delay-network structure and apply genetic algorithms (GA) to optimize a subset of the FDN parameters. In [13], a GA is used to find both the N^2 coefficients of the feedback matrix $\mathbf{A}$ and N cutoff frequencies of lowpass filters, one for each delay line. The authors of [14] aim at finding a mapping between room and FDN parameters for VR/AR applications. To this end, they synthesize the binaural RIR of a set of virtual shoebox rooms, apply a GA to tune the FDN’s delay lines and scalar feedback gain, and use the resulting training pairs to fit a support vector machine (SVM) regressor. In [15], Coggin and Pirkle apply a GA for the estimation of $\mathbf{m}$, $\mathbf{b}$, and $\mathbf{c}$. For every individual in a generation, attenuation and output filters are designed using the Yule-Walker method. The authors investigate several fitness functions before favoring the Chebyshev distance between the power envelopes

of the target and predicted IR. The optimization is run for late reverberation only: the first 85 ms of the RIR are cut and convolved with the input signal, before being fed to the FDN to model late reverberation. Following [15], Ibnayhya and Reiss [16] recently introduced a multi-stage method combining more advanced analytical filter design methods and GAs to estimate the FDN parameters that would best approximate a target RIR in terms of a MFCC-based fitness function, similarly to the cost function used in [26].

Due to the well-known limitations of genetic algorithms, such as the high risk of finding sub-optimal solutions, overall slow convergence rate, and the challenges of striking a good exploration-exploitation balance [30], gradient-based techniques have been recently proposed.

Inspired by groundbreaking research on differentiable digital signal processing [31], Lee et al. [17] let the gradients of a multiresolution spectral loss flow through a differentiable artificial reverberator so that they may reach a trainable neural network tasked with yielding the reverberator parameters. This way, the authors train a convolutional-recurrent neural network tasked with inferring the input, output, and absorption filters of a FDN from a reference reverberation (RIR or speech). It is worth mentioning, however, that it is not the delay-network parameters those that are optimized via stochastic gradient descent, but rather it is the weights of the neural network serving as black-box parameter estimator. As such, the differentiable FDN is effectively used as a processing block in computing the loss of an end-to-end neural network instead of being the target of the optimization process.

In a different vein, several recent works aim at learning lumped parameters via gradient-based optimization directly within the digital structure of the model, and forgo parameter-yielding neural networks altogether. In this respect, automatic differentiation has been recently proposed to find $\mathbf{A}, \mathbf{b}, \mathbf{c}$ of an FDN (without parameterizing them as a neural network) so as to minimize spectral coloration and obtain a flat frequency response [18]. Similar yet distinct, other works adopt a white-box system identification approach and use backpropagation to find the parameters of predetermined mathematical models so as to

match measured data as closely as possible [19, 32, 33].

In this work, we adopt the latter approach and use the method detailed in the next section to find the values of $\mathbf{A}$, $\mathbf{b}$, $\mathbf{c}$, $\mathbf{m}$, and d such that the resulting FDN is capable of modeling perceptually meaningful characteristics of the acoustic response of real-life environments

4 Proposed Method

The proposed method involves an iterative gradient-based optimization algorithm. As a learning objective, we choose a perceptually-informed loss function, $\mathcal{L}(h, \hat{h})$, between a target RIR, $h[n]$, and the time-domain FDN output, $\hat{h}[n]$, obtained by setting the FDN input to the Kronecker delta, i.e., $u[n] = \delta[n]$.

We initialize the FDN parameters with no prior knowledge of $h[n]$. Then, at the beginning of each iteration, we calculate $\hat{h}[n]$ by evaluating (1) while freezing the current parameter estimates. Thus, we evaluate $\mathcal{L}(h, \hat{h})$. Finally, each trainable FDN parameter θ undergoes an optimization step using the error-free gradient $\nabla_{\theta} \mathcal{L}$ computed via reverse-mode automatic differentiation [20].

A typical approach is to use a delay network to only model the late reverberation while handling early reflections separately [12, 14–16]. Instead, we optimize the FDN such that it accounts for both early and late reverberation at the same time, exploiting thus the advantages of synthesizing the entire RIR with an efficient recursive structure.

At training time, we strip out the initial silence due to direct-path propagation, and disregard every sample beyond the T_{60} of the target RIR. In other words, we only consider the first $L_{T_{60}} := \lceil T_{60} \cdot f_s \rceil$ samples of $h[n]$ and $\hat{h}[n]$ in computing the loss. The reason behind restricting the temporal scope only to the segment of the RIR associated with the T_{60} is that, beyond this point, the values involved in the ensuing computations become so small that numerical errors might occur when using single-precision floating-point numbers, and the training process would unwantedly focus on the statistics of background/numerical noise. Notice that, at inference time, i.e., once the FDN parameters have been learned, the room acoustics simulation can be run indefinitely at a very low computational cost.

In this work, we optimize the input gains $\mathbf{b} \in \mathbb{R}_{\geq 0}^N$, the output gains $\mathbf{c} \in \mathbb{R}_{\geq 0}^N$, the direct gain $d \in \mathbb{R}_{\geq 0}$, the feedback matrix $\mathbf{A} \in \mathbb{R}^{N \times N}$, and the delays $\mathbf{m} \in \mathbb{R}_{\geq 0}^N$ expressed in fractional samples.

4.1 Model Reparameterization

Let θ be a scalar parameter of the FDN such that $\theta \in \mathbb{X}$ where $\mathbb{X} \subseteq \mathbb{R}$. In general, instead of learning θ directly, we learn an unconstrained proxy $\tilde{\theta} \in \mathbb{R}$ that maps onto θ through a differentiable (and possibly nonlinear) function $f : \mathbb{R} \rightarrow \mathbb{X}$. Hence, we can use $f(\tilde{\theta})$ in place of θ in any computation involved in the forward pass of the FDN. In case of vector-valued parameters $\boldsymbol{\theta} \in \mathbb{X}^N$, we apply f in an element-wise fashion, i.e., $\boldsymbol{\theta} := [f(\tilde{\theta}_1), \dots, f(\tilde{\theta}_N)]^T$.

The reason behind such an explicit reparameterization method is that, while we would like $\boldsymbol{\theta}$ to take values in $\mathbb{X}^N$ at every iteration, gradient-based optimization may yield parameters that do not respect such a constraint, even when using implicit regularization strategies, e.g., by means of auxiliary loss functions and regularizers.

In our FDN model, we treat every parameter in a different fashion. We discuss gain reparameterization in Section 4.2 and present the feedback matrix reparameterization in Section 4.3. Finally, we outline the implementation of the differentiable delay lines and their reparameterization in Section 4.4.

4.2 Trainable Gains

We would like the input, output, and direct gains of our differentiable FDN to be nonnegative. This way, the gains only affect the amplitude of the signals and do not risk inverting their polarity. Instead, we let $\mathbf{A}$ model phase-reversing reflections. To enforce gain nonnegativity, we employ a differentiable nonlinear function $f_{\geq 0} : \mathbb{R} \rightarrow \mathbb{R}_{\geq 0}$, such as, e.g., the Softplus or exponential function. We then learn, e.g., $\tilde{\mathbf{b}} = [\tilde{b}_1, \dots, \tilde{b}_N]^T$ while using $\mathbf{b} = [f_{\geq 0}(\tilde{b}_1), \dots, f_{\geq 0}(\tilde{b}_N)]^T$ in every computation concerning the FDN. Among other options, we select $f_{\geq 0}(x) = |x|$ [19], where the requirement of $f_{\geq 0}$ being differentiable everywhere was relaxed as it is common for many widely-adopted activation functions, such as ReLU.

4.3 Trainable Feedback Matrix

We focus on lossy FDNs. In prior work [18], frequency-independent homogeneous decay has been modeled by parameterizing $\mathbf{A}$ as the product of a unilossless matrix $\mathbf{U}$ and a diagonal matrix $\boldsymbol{\Gamma}(\mathbf{m}) = \text{diag}(\gamma_1, \dots, \gamma_N) = \text{diag}(\gamma^{m_1}, \dots, \gamma^{m_N})$ containing a delay-dependent absorption coefficient for each delay line, where $\gamma \in (0, 1)$ is a constant gain-per-sample coefficient. The feedback matrix is thus expressed as

$$\mathbf{A} = \mathbf{U}\boldsymbol{\Gamma}(\mathbf{m}). \quad (2)$$

We let $\mathbf{U}$ be an orthogonal matrix, satisfying the unitary condition for unilosslessness [34]. To ensure this property, $\mathbf{U}$ is further parameterized by means of $\tilde{\mathbf{W}} \in \mathbb{R}^{N \times N}$ that, at each iteration, yields [18]

$$\mathbf{U} = \exp(\mathbf{W}_{\text{Tr}} - \mathbf{W}_{\text{Tr}}^T), \quad (3)$$

where $\mathbf{W}_{\text{Tr}}$ is the upper triangular part of $\tilde{\mathbf{W}}$, and $\exp(\cdot)$ is the matrix exponential. In other words, instead of trying to directly learn a unilossless matrix, we learn an unconstrained real-valued matrix $\tilde{\mathbf{W}}$ that maps onto an orthogonal matrix through the exponential mapping in (3).¹ In particular, $\mathbf{U}$ is ensured to be orthogonal because $\mathbf{W}_{\text{Tr}} - \mathbf{W}_{\text{Tr}}^T$ is skew-symmetric [35].

As for the matrix $\boldsymbol{\Gamma}(\mathbf{m})$, we noticed that tying the values of the absorption coefficients $\gamma_1, \dots, \gamma_N$ to those of the fractional delays $m_1, \dots, m_N$ led to instability during training since the values in $\mathbf{m}$ were concurrently acting on the temporal location of the IR taps as well as their amplitude.² Conversely, we decouple $\boldsymbol{\Gamma}$ from $\mathbf{m}$, thus learning a possibly inhomogeneous FDN characterized by $\mathbf{A} = \mathbf{U}\boldsymbol{\Gamma}$, as opposed to the homogeneous FDNs studied in [18].

In learning the unconstrained absorption matrix $\tilde{\boldsymbol{\Gamma}} = \text{diag}(\tilde{\gamma}) = \text{diag}(\tilde{\gamma}_1, \dots, \tilde{\gamma}_N)$, we define $f_{(0,1)} : \mathbb{R} \rightarrow (0, 1)$ and optimize $\tilde{\gamma} \in \mathbb{R}^N$ so that $\boldsymbol{\Gamma} = \text{diag}(f_{(0,1)}(\tilde{\gamma}_1), \dots, f_{(0,1)}(\tilde{\gamma}_N))$. In the following, we use the well-known Sigmoid function to

¹It is worth noting that, although $\tilde{\mathbf{W}}$ is a $N \times N$ matrix, only the $N(N-1)/2$ upper triangular entries are actually learned and used in downstream computations.

²Notice that this problem is unique to our approach, as previous studies employed non-trainable delay lines with fixed lengths [18].

force the absorption coefficients to take values in the range of 0 to 1, i.e.,

$$f_{(0,1)}(x) = \frac{1}{1 + e^{-x}}. \quad (4)$$

4.4 Trainable Delay Lines

In the digital domain, an integer delay can be efficiently implemented as a reading operation from a buffer that accumulates past samples. Unfortunately, this approach is non-differentiable. Instead, since the Fourier transform is a linear and differentiable operator, we may think to work in the frequency domain to circumvent such a problem. In particular, we evaluate the delays on the unit circle at discrete frequency points $\omega_k = 2\pi k/K$, for $k = 0, \dots, K-1$.

Each differentiable delay line embeds a K -sample buffer. First, we compute the Fast Fourier Transform (FFT) of the signal $x[n]$ currently stored in the buffer. Then, we apply a (fractional) delay of m samples by multiplying the resulting spectrum with the complex exponential $e^{-j\omega_k m}$. Finally, we go back in the time domain by computing the inverse FFT. We can express this sequence of differentiable operations as

$$x[n-m] = \frac{1}{K} \sum_{k=0}^{K-1} \underbrace{\left(\sum_{\tau=0}^{K-1} x[\tau] e^{-j\omega_k \tau} \right)}_{\text{FFT}\{x[n]\}} e^{j\omega_k (n-m)} \quad (5)$$

Optionally, cosine-tapered windows can be included in (5) to reduce spectral leakage. Nevertheless, preliminary experiments involving Hann windowing showed no meaningful improvement in the method's performance.

Delays must be nonnegative to realize a casual system. Hence, we use $f_{\geq 0}$ to ensure nonnegativity of the fractional delays, i.e., $m_i = f_{\geq 0}(\tilde{m}_i)$ where $\tilde{m}_i \in \mathbb{R}$ is the i th trainable delay-line length proxy, $i = 1, \dots, N$. Notice that such a parameterization, while enforcing nonnegativity, imposes no upper bound on m_i . An alternative parameterization is $m_i = K \cdot f_{(0,1)}(\tilde{m}_i)$, which ensures that $m_i \in (0, K)$ at all times. In this work, we favored the former for its lower computational cost.

Finally, it is worth highlighting three main reasons for labeling our FDN model as *time-domain*, despite the implementation of differentiable delay lines in the frequency domain. First,

frequency-domain operations are confined within the delay filterbank. Second, we stress that our FDN yields the output one sample at a time according to (1). Third, we emphasize the difference between our approach and existing methods implementing every FDN operation in the frequency domain [17, 18].

4.5 Loss Function

Our goal is to learn an FDN capable of capturing perceptual qualities of a target room. Hence, we avoid pointwise regression objectives such as L^p -losses between IR taps. Instead, we set out to minimize an error function ($\mathcal{L}_{\text{EDC}}$) between the true and predicted EDCs. Additionally, we use a novel regularization loss ($\mathcal{L}_{\text{EDP}}$) aimed at matching the echo distribution of the target RIR by acting on the normalized EDP. Namely, the composite loss function can be written as

$$\mathcal{L} = \mathcal{L}_{\text{EDC}} + \lambda \mathcal{L}_{\text{EDP}}, \quad (6)$$

where $\lambda \in \mathbb{R}_{\geq 0}$. Similarly to [19], the loss is evaluated in the time domain, and, at each iteration, requires a forward pass through the discrete-time model defined by the current parameter estimates. In the following sections, we will analyze each of the terms in (6).

4.5.1 Energy Decay Curve Loss

For a discrete-time RIR of length L , the EDC can be computed through Schroeder's backward integration [36]

$$\varepsilon[n] = \sum_{\tau=n}^L h^2[\tau]. \quad (7)$$

Since (7) is differentiable, we can train the FDN to minimize a normalized mean squared error (NMSE) loss defined on the EDCs, i.e.,

$$\mathcal{L}_{\text{EDC}} = \frac{\sum_n (\varepsilon[n] - \hat{\varepsilon}[n])^2}{\sum_n \varepsilon[n]^2}, \quad (8)$$

where $\hat{\varepsilon}[n] = \sum_{\tau=n}^L \hat{h}^2[\tau]$.

It is worth noting that, whereas the EDC is typically expressed in dB, (8) is evaluated on a linear scale. The idea is that a linear loss emphasizes errors in the early portion of $\varepsilon[n]$, i.e., where

discrepancies are more perceptually relevant [37], compared to a logarithmic loss that would put more focus on the reverberation tail.

4.5.2 Differentiable Normalized Echo Density Profile

In [21], Abel and Huang introduced the so-called normalized echo density profile (EDP) as a means to quantify reverberation echo density by analyzing consecutive frames of the reverberation impulse response. The EDP indicates the proportion of impulse response taps that fall above the local standard deviation. The resulting profile is normalized to a scale ranging from nearly zero, indicating a minimal presence of echoes, to around one, denoting a fully dense reverberation with Gaussian statistics [38].

The EDP is defined as [21]

$$\eta[n] = \frac{1}{\text{erfc}(1/\sqrt{2})} \sum_{\tau=n-\nu}^{n+\nu} w[\tau] \mathbb{1}\{|h[\tau]| > \sigma_n\}, \quad (9)$$

where $\text{erfc}(\cdot)$ is the complementary error function,

$$\sigma_n = \sqrt{\sum_{\tau=n-\nu}^{n+\nu} w[\tau] h^2[\tau]}, \quad (10)$$

is the standard deviation of the n th frame, $w[n]$ is a window function of length $2\nu + 1$ samples (usually 20 ms) such that $\sum_{\tau} w[\tau] = 1$, and $\mathbb{1}\{\cdot\}$ is an indicator function

$$\mathbb{1}\{|h[\tau]| > \sigma\} = \begin{cases} 1 & |h[\tau]| > \sigma, \\ 0 & |h[\tau]| \leq \sigma. \end{cases} \quad (11)$$

Notably, $\mathbb{1}\{\cdot\}$ is non-differentiable. Thus, the EDP cannot be utilized within our automatic differentiation framework.

To overcome this problem, this section introduces a novel differentiable EDP approximation, which we call *soft echo density profile*.

First, we notice that the indicator function $\mathbb{1}\{|h[\tau]| > \sigma\}$ can be equivalently expressed as a Heaviside step function $\mathcal{H}(|h[\tau]| - \sigma)$. Then, we let $g(x)$ denote the Sigmoid function. We define the *scaled Sigmoid* function $g_{\kappa}(x) = g(\kappa x)$, where $\kappa \in \mathbb{R}_{\geq 0}$. Since

$$\lim_{\kappa \rightarrow \infty} g_{\kappa}(x) = \mathcal{H}(x), \quad (12)$$

we can define the Soft EDP function as

$$\eta_{\kappa}[n] = \frac{1}{\text{erfc}(1/\sqrt{2})} \sum_{\tau=n-\nu}^{n+\nu} w[\tau] g_{\kappa}(|h[\tau]| - \sigma_n), \quad (13)$$

which approximates (9) for $\kappa \gg 1$.

It is worth mentioning that, whilst the EDP approximation improves as κ becomes larger, this also has the side effect of increasing the risk of vanishing gradients. In fact, the derivative of the scaled Sigmoid function can be written as

$$g'_{\kappa}(x) = g(\kappa x) (1 - g(\kappa x)), \quad (14)$$

which approaches zero for large or small inputs. Hence, $g'_{\kappa}(x)$ takes on near-zero values outside of a neighborhood of $x = 0$ whose size is inversely proportional to κ , which, in turn, may impede the gradient flow for $\kappa \gg 1$.

In practice, we would like to choose a large value of κ but not larger than what is needed. Notably, the need for a large scaling factor is not constant throughout the temporal evolution of a RIR. Early taps are typically sparse, and $(|h[\tau]| - \sigma_n)$ tends to fall within the saturating region of $g_{\kappa}(\cdot)$, even for lower values of κ . Conversely, in later portions of the RIR, κ must take on very large values to contrast the fact that the amplitude of $(|h[\tau]| - \sigma_n)$ progressively decreases. For this reason, we introduce a time-varying scaling parameter, $\kappa_n = \xi n + \varrho$, where $\xi \in \mathbb{R}_{>0}$ and $\varrho \in \mathbb{R}_{\geq 0}$ are hyperparameters. Progressively increasing the scaling coefficient has the benefit of enhancing the gradient flow for early decay, while improving the EDP approximation for late reverberation. In general, a more principled definition for κ_n could be devised, e.g., by tying it to the local statistics of the target RIR or its energy decay. In this work, however, we favor a simple and reproducible approach as it proved to work well in practice.

4.5.3 Soft EDP Loss

Despite the existing trade-off between vanishing gradients and goodness of fit, every operation involved in the computation of (13) is differentiable. This allows us to use the following EDP




Fig. 2 Summary of the proposed FDN model.

loss term as a regularizer during the FDN training

$$\mathcal{L}_{\text{EDP}} = \frac{1}{L_{T_{60}}} \sum_n (\eta_\kappa[n] - \hat{\eta}_\kappa[n])^2, \quad (15)$$

where $\hat{\eta}_\kappa[n]$ is the Soft EDP of the predicted RIR, and $L_{T_{60}} = \lceil T_{60} \cdot f_s \rceil$.

4.5.4 Model Summary

Figure 2 summarizes the proposed differentiable FDN model, listing all the unconstrained trainable parameters (top), their dimension, the corresponding reparameterization (middle), and illustrating once again how, through (1), the FDN processes time-domain signals, including unit impulses $\delta[n]$ (bottom).

5 Evaluation

We evaluate the proposed method using real-world measured RIR from the 2016 MIT Acoustical Reverberation Scene Statistics Survey [39]. The MIT corpus contains single-channel environmental IRs of both open and closed spaces. Of the 271 IRs, we select three according to their reverberation time, which, across the dataset, ranges from a minimum of 0.06 s to a maximum of 1.99 s. We select three indoor environments, namely, (i) a small room ($T_{60} \approx 0.2$ s), (ii) a medium room ($T_{60} \approx 0.6$ s), and (iii) a larger room ($T_{60} \approx 1.2$ s). For reproducibility, the ID of the chosen

RIRs is reported: (i) `h214.Pizzeria_1txts`, (ii) `h270.Hallway_House_1txts`, and (iii) `h052.Gym_WeightRoom_3txts`. The full IR Survey dataset is available online.³ For the evaluation, all IRs are resampled to 16 kHz and scaled to unit norm.

5.1 Baseline Methods

From the overview presented in Section 3, it appears that no method in the literature is directly comparable with ours. In fact, existing automatic tuning approaches either focus on off-the-shelf reverb plug-ins [12, 26], limit the set of target parameters to just a few [13, 14], or augment the FDN topology with auxiliary frequency-dependent components [15, 16]. To the best of our knowledge, there is no state-of-the-art method addressing the simultaneous estimation of every FDN parameters in a purely data-driven fashion.

That being said, with the aim of comparing our approach with existing techniques, we implement three baseline methods.

The first is based on a classic method for homogeneous reverberation time control (HRTC), and involves choosing all FDN parameters but the absorption coefficients heuristically. For simplicity, we refer to this method as “HRTC baseline.”

The second method, which we call “Colorless baseline,” also relies on HRTC to control the decay rate. However, contrary to the HRTC baseline, all remaining FDN parameters are optimized following the approach detailed in [18] as so to achieve a maximally flat frequency response.

The third and final baseline makes use of a genetic algorithm (GA) inspired by [16] to optimize every FDN parameter except for the feedback matrix. We call this method “GA baseline.”

In the following sections, we will detail the three baseline methods one at a time.

5.1.1 HRTC Baseline

Given the FDN model shown in Figure 1, a classic method to introduce homogeneous loss in an otherwise lossless prototype is to replace each unit delay z^{-1} with a lossy delay element γz^{-1} , where γ is thought of as a gain-per-sample coefficient [7, 18, 40].

³[Online] IR Survey dataset: https://mcdermottlab.mit.edu/Reverb/IR_Survey.html

In practice, the loss of each delay line is lumped into a single attenuation term proportional to its length. We can thus define $\mathbf{\Gamma}(\mathbf{m}) = \text{diag}(\gamma^{m_1}, \dots, \gamma^{m_N})$ as discussed in Section 4.3, where γ controls the decay rate according to the desired reverberation time. Namely, γ should satisfy [7]

$$20 \log_{10} \gamma = \frac{-60}{f_s T_{60}}, \quad (16)$$

where T_{60} is estimated from the target RIR.

Whereas the absorption coefficients are given by (16), every other parameter in the HRTC baseline are determined by means of heuristics. We parameterize the feedback matrix as in (2), where $\mathbf{U}$ is a random orthogonal matrix. To ensure that the HRTC baseline is most comparable with the proposed method (Section 4.3) and the Colorless baseline (Section 5.1.2), we obtain $\mathbf{U}$ through the exponential mapping in (3). The scalar gain d is set equal to the amplitude of the target RIR at the time index associated with the direct path. We use unity input gains, i.e., $\mathbf{b} = \mathbf{1}_N$, where $\mathbf{1}_N$ is a vector of $N = 6$ ones. The output gains are chosen so that $\mathbf{c} = \frac{1}{N} \mathbf{1}_N$. As such, the dot product $\mathbf{c}^T \mathbf{s}[n]$ in (1) is equivalent to the arithmetic average of the outputs of the N delay lines at time n . Finally, the delays $\mathbf{m} = [997, 1153, 1327, 1559, 1801, 2099]$ consist of the logarithmically distributed prime numbers from Delay Set #1 in [18].

5.1.2 Colorless Baseline

In the previous section, we discussed a baseline method consisting of a homogeneous FDN where the reverberation time is controlled by choosing γ according to (16), with the other parameters being manually selected. Here, we present an alternative baseline method that foregoes some of these arbitrary choices in favor of an optimization approach.

In [18], the authors implement a differentiable homogeneous FDN in the frequency domain and find $\mathbf{A}$, $\mathbf{b}$, and $\mathbf{c}$ via gradient descent so as to minimize spectral coloration.

Colorless reverberation [41] is defined as the acoustic quality of an artificial reverberation algorithm whose frequency response is flat, i.e., constant at all frequencies.

To achieve this, $\mathbf{A}$, $\mathbf{b}$, and $\mathbf{c}$ are iteratively updated via backpropagation using Adam [42] to

minimize a reference-free⁴ loss function comprising two terms [18]. The first term encourages the magnitude of the sampled transfer function to be as close to one as possible. The second term penalizes IR sparsity in the time domain and avoids trivial solutions.

The delays $\mathbf{m}$ are kept constant, and $\mathbf{A}$ is parameterized through (2) and (3). Like in the HRTC baseline, we use the lengths in samples comprised in Delay Set #1 from [18], and γ is set according to (16).

With this baseline, our goal is to test whether an FDN optimized to obtain a flat magnitude response brings about any benefit when it comes to modeling the energy decay and echo density of a target RIR. It is worth noting, however, that the learning objective in [18] is not concerned with matching the behavior of a reference RIR. As such, the resulting $\mathbf{A}$, $\mathbf{b}$, and $\mathbf{c}$ might prove suboptimal for what concerns reproducing the reverberation time of the target space.

5.1.3 GA Baseline

In [16], Ibnyahya and Reiss proposed a multi-stage automatic tuning approach that combines genetic optimization [43] and analytical filter design [44]. The prototype FDN considered in [16] is equipped with attenuation filters $H_i(z)$ controlling the decay rate and a tone-correction filter $T(z)$ [45]. We depict the model architecture with $N = 3$ in Figure 3, featuring the output filter and graphic equalizers for each delay line (cf. Figure 1). Our implementation uses $N = 6$.

As in [16], we aim to optimize $\mathbf{m}$, $\mathbf{b}$, $\mathbf{c}$, and d , whereas $\mathbf{A}$ is fixed throughout the procedure. The GA is run for 50 generations (i.e., ten times more than in [16]), each with a population of 50 FDNs. Each FDN is therefore an *individual* characterized by $3N + 1$ mutable parameters, namely, $\mathbf{m}$, $\mathbf{b}$, $\mathbf{c}$, and d . During the optimization, scalar gains are constrained to take values in $[-1, 1]$. Similarly, delays are constrained to take values in the range of 200 μ s to 64 ms. The attenuation filters are analytically determined according to the individual's delay values in $\mathbf{m}$ and the desired octave-band reverberation times [44]. In turn, the

⁴With *reference-free*, we emphasize that, unlike our method, the loss function in [18] is computed solely on the FDN response, and does not consider a reference RIR as the target of the optimization process.




Fig. 3 Block diagram of the prototype FDN used in [16] with $N = 3$.

output graphic EQ filter [46] is found based on the initial level of the desired octave-band EDCs. All individuals implement the same random orthogonal feedback matrix [47], which is not affected by genetic optimization. The fitness of each individual at every generation is assessed through the mean absolute error between the MFCCs of the target RIR and those of the FDN output [16].

In our implementation, we avail of the Feedback Delay Network Toolbox by S. J. Schlecht [40] for fitting the graphic EQ filters and implementing the FDN, and use the GA solver included in MATLAB’s Global Optimization Toolbox for finding $\mathbf{m}$, $\mathbf{b}$, $\mathbf{c}$, and d .

It is worth emphasizing the differences between the prototype FDN used in [16] (Figure 3) and the proposed delay network (Figure 1). First, [16] does not optimize the feedback matrix $\mathbf{A}$, whereas we do. Second, [16] relies on IIR filters to achieve the desired reverberation time, whereas our model does not. Introducing $H_i(z)$ and $T(z)$ makes the baseline arguably more powerful in modeling a target RIR. At the same time, though, prior knowledge must be injected into the model by means of filter design to successfully run the GA and obtain meaningful results in a reasonable number of generations.

5.2 Evaluation Metrics

As evaluation metrics, we select the T_{20} , T_{30} , and T_{60} , i.e., the reverberation time extrapolated considering the normalized IR energy decaying from -5 dB to -25 dB, -35 dB, and -65 dB, respectively. Ideally, these three metrics are the same if the energy decay exhibits a perfectly linear slope. In practice, this is often not the case, as it can be seen, e.g., in Figure 10. Hence, we believe that it is more informative to report all three of

Table 1 Reverberation time, loss values, iteration indices, composite loss function weights, and average time per training step. Iterations denoted with (0) indicate pre-training random initialization.

	T_{60}	iter	$\mathcal{L}$	$\mathcal{L}_{\text{EDC}}$	$\mathcal{L}_{\text{EDP}}$	λ	s/iter
Gym	1.225	(0) 279	1.2070 0.0201	0.9876 0.0091	0.2194 0.011	1	23.73
Hallway	0.607	(0) 340	1.0205 0.0057	0.9904 0.0052	0.3013 0.0046	0.1	11.68
Pizzeria	0.206	(0) 583	0.9589 0.0781	0.9345 0.0766	0.2443 0.0154	0.1	4.36

them, as together they provide a richer insight into the global behavior of the EDC as it approaches the -60 dB threshold. It is also worth pointing out that it is unclear whether the T_{60} is entirely reliable in measuring the reverberation time of real-world RIRs due to the often non-negligible noise floor.

Furthermore, we report the following ISO 3382 measures: *Clarity* (C_{80}), expressed in dB, *Definition* (D_{50}), expressed as a percentage, and *Center time* (t_s), expressed in ms. Defined $L_\tau := \lceil \tau \cdot f_s \cdot 10^{-3} \rceil$, these metrics are given by [48]

$$C_{80} = 10 \log_{10} \frac{\sum_{n=0}^{L_{80}-1} h^2[n]}{\sum_{n=L_{80}}^{L-1} h^2[n]}, \quad (17)$$

$$D_{50} = 100 \cdot \frac{\sum_{n=0}^{L_{50}-1} h^2[n]}{\sum_{n=0}^{L-1} h^2[n]}, \quad (18)$$

$$t_s = 10^3 \cdot \frac{\sum_{n=0}^{L-1} n \cdot h^2[n]}{f_s \cdot \sum_{n=0}^{L-1} h^2[n]}. \quad (19)$$

For all metrics considered, we report the error with respect to the target values. Absolute deviations are denoted by Δ in Tables 2, 3, and 4.

Finally, it is worth pointing out that the EDPs shown in the following sections are obtained using the (non-differentiable) formulation given in (9), unless explicitly stated otherwise.

5.3 Parameter Initialization

We initialize the differentiable FDN parameters as follows. We let $\tilde{\mathbf{b}}^{(0)} \sim \mathcal{N}(\mathbf{0}, \frac{1}{N} \mathbf{I}_N)$, where $\mathbf{I}_N$ is the $N \times N$ identity matrix. We let $\tilde{\mathbf{c}}^{(0)} = \frac{1}{N} \mathbf{1}_N$, where $\mathbf{1}_N$ is a vector of N ones. We set $\tilde{d}^{(0)} = 1$. We initialize $\tilde{\mathbf{W}}^{(0)}$ and $\tilde{\mathbf{\Gamma}}^{(0)}$ so that $\tilde{\mathbf{W}}_{ij}^{(0)} \sim \mathcal{N}(0, \frac{1}{N})$ and $\tilde{\gamma}_i^{(0)} \sim \mathcal{N}(0, \frac{1}{N})$. We initialize $\tilde{\mathbf{m}}^{(0)}$




Fig. 4 Gym (h052) EDCs.




Fig. 5 Gym (h052) EDPs.

so that $\tilde{m}_i^{(0)} = \psi \tilde{m}_i^*$ with $\tilde{m}_i^* \sim \text{Beta}(\alpha, \beta)$, for $i = 1, \dots, N$, where $\alpha \geq 1$ and $\beta > \alpha$. We empirically set $\psi = 1024$, $\alpha = 1.1$, and $\beta = 6$ to ensure a maximum possible delay of 64 ms (the same as in the GA baseline) and a mean value of about 10 ms. We let the Sigmoid scaling term κ_n increase linearly from 10^2 to 10^5 as $n = 0, \dots, L_{T_{60}} - 1$. Finally, we choose the hyperparameter λ for each test case (see Table 1) in order to balance the two terms in (6).

5.4 Implementation Details

We implement our differentiable model in Python using PyTorch. We define the FDN as a class inheriting from `nn.Module`. We thus define the unconstrained trainable parameters as instances of `nn.Parameter`. Our model operates at a sampling rate of 16 kHz. As a result, its memory footprint turns out to be contained, allowing us to train all




Fig. 6 Gym (h052) IRs.

FDNs considered in the present study on a single NVIDIA Titan V graphics card.⁵ We optimize the models for a maximum of 650 iterations using Adam [42] with a learning rate of 0.1, $\beta_1 = 0.9$, $\beta_2 = 0.999$, and no weight decay. The average training time per iteration is reported in Table 1. At each step, approximately 25% of the time is taken by the forward pass of the FDN, just below 20% is spent computing the loss function, and just above 55% is spent backpropagating the gradients and updating the parameters. Notably, we observe that the computation time increases linearly with the estimated T_{60} . For each test case, we present the model with the lowest composite loss.

5.5 Test Case: Gym (h052)

We start by considering the Gym RIR (h052). The FDN is trained setting $\lambda = 1$, i.e., equally weighting $\mathcal{L}_{\text{EDC}}$ and $\mathcal{L}_{\text{EDP}}$. As shown in Table 1, the best model is reached at iteration 279, after the loss has decreased by two orders of magnitude with respect to the initial value obtained with the random initialization described in Section 5.3. Here, we present a comparison between the target room acoustics (solid black line), the GA baseline [16] (dotted blue line), the HRTC baseline (dash-dotted green line), the Colorless baseline [18]

⁵Preliminary experiments carried out with increased computational resources indicate that results comparable with those reported in the present study can be obtained at a sampling rate of 48 kHz.




Fig. 7 Hallway (h270) EDCs.




Fig. 8 Hallway (h270) EDPs.

(dash-dotted blue line), and, finally, the proposed differentiable FDN (dashed orange line).

Figure 4, 5, and 6 show that the proposed method is capable of closely matching the EDC, EDP, and envelope of the target RIR, respectively.

Conversely, the baseline methods produce poorer results. In Figure 4, we may notice, in fact, that the EDC of the GA baseline deviates from that of the target RIR after just below 150 ms. The energy decay of the HRTC method, instead, is matched just for the very first few ms, showing to part from the target immediately after and then linearly decaying. It is interesting to notice that the Colorless method, although sharing some parameters with HRTC, behaves completely different. In fact, after an initial overshoot, said baseline is able to match the target decay till 400 ms, where it starts to exhibit a less steep decay. Such a difference is due to the feedback matrix and input/output gains being optimized to




Fig. 9 Hallway (h270) IRs.

get a colorless IR, unveiling their importance for obtaining a correct time decay.

Furthermore, the EDP of the baseline methods indicate a scarce echo density in the first 250 ms, especially for HRTC and Colorless. The output of the FDN obtained with GA, instead, becomes identically zero just after approximately 0.9 s. The ensuing EDP pathologies are confirmed by the IR depicted in Figure 6, where the baselines are shown to yield fewer, more prominent taps compared to the IR of the proposed FDN model.

Notably, however, Figure 6 also suggests that both the proposed and baseline methods estimate a larger d than what would correctly render the direct sound. We attribute this phenomenon to an attempt at compensating the lack of a noise floor that, in real-life measurements, contributes to the total energy of the RIR. We argue that, in FDN models with tunable direct gain, offsetting this bias is naively achieved by increasing d .

As far as reverberation metrics are concerned, Table 2 shows that the proposed method has an overall better performance, with a ΔT_{30} , ΔD_{50} and Δt_s of 2.5 ms, 0.73%, and 59 μ s, respectively. The T_{20} is estimated with an error of 100 ms, i.e., approximately 2.3 and 4 times lower than those of the GA and HRTC methods, respectively. As for this metric, our method is second only to the Colorless method, whose $\Delta T_{20} = 15$ ms. Similarly, as far as T_{60} is concerned, the proposed approach is surpassed only by the HRTC method that shows a $\Delta T_{60} = 6.8$ ms; this is expected given that the parameter γ is specifically designed to match the




Fig. 10 Pizzeria (h214) EDCs.




Fig. 11 Pizzeria (h214) EDPs.

target T_{60} . Finally, our method shows the second best ΔC_{80} overcome only by GA's, with a difference of just 0.13 dB.

5.6 Test Case: Hallway (h270)

Let us now consider the Hallway RIR (h270), which is characterized by nearly half the T_{60} of the previous case. Table 1 shows that the best results are obtained at iteration 340, where the loss is again lower by two orders of magnitude with respect to the starting point.

Figure 7 reports the EDCs of target, baselines, and proposed methods following the color conventions reported in the previous subsection. Once again, we evince the good matching between our and target decays, as they start to part around 0.4 s where the residual energy of the predicted RIR is low, i.e., around -40 dB. Instead, HRTC and Colorless methods present a sharp drop of energy after the direct path, which results into




Fig. 12 Pizzeria (h214) IRs.

IRs characterized by an almost total absence of reflections for the first few ms, as shown in Fig. 9. Then, HRTC presents an overshoot that lasts till 350 ms, after which it starts to match the target EDC. However, this happens when the energy has already reached -40 dB, thus after virtually all early reflections have occurred. In addition, the Colorless and GA baselines are not able to correctly match the decay in time except for a small span of time around 100 ms.

The EDPs depicted in Figure 8 indicate that our approach is able to generate a close match with the target EDP, further validating the effectiveness of proposed Soft EDP loss function. Indeed, the orange dashed curve nicely follows the target curve until the T_{60} ; we remind, in fact, that the training is performed only on such a span of time. Instead, the EDP of the baseline methods show low values in the first 200 ms compared to the target one, and afterward, even if they take on comparable values, they do not follow the same trend. This is confirmed by the RIRs shown in Figure 9. Indeed, even in this test case, the FDN optimized by means of the proposed approach has an IR that resembles more of a realistic RIR, even though the amplitude of individual taps is not entirely matched.

Table 3 reports the reverberation metrics. We can observe that the proposed optimization approach yields better results with respect to the previous case. Notably, the proposed optimization performs better than the three baselines for all the metrics but the T_{60} , for which, as expected,

the HRTC method shows the lowest error, with a ΔT_{60} of 11 ms against the 95.6 ms obtained with our approach. Then, the error ΔC_{80} associated with the clarity index is three orders of magnitude less than what can be achieved with the GA and HRTC methods, and two orders of magnitude less than Colorless'. In addition, the error Δt_s on the center time reaches 32 μ s, while all the baselines have a greater error, shifting the center of mass of the predicted IR energy more toward the reverberation tail.

5.7 Test Case: Pizzeria (h214)

Finally, let us address the shortest RIR of the ones considered in the present study, i.e., h214, having a T_{60} of just above 0.2 s.

Here, all the baseline methods appear to fail at modeling the target room. In particular, the IRs shown in Figure 12 exhibit a few sparse taps, being thus far from resembling a real RIR. Since the backward-integrated energy abruptly decays with every peak, this results in a staircase-like behavior of the EDC depicted in Figure 10.

Facing the same difficulties, the proposed optimization method takes more gradient steps compared to the previous two test cases before converging at iteration 583.

In Figure 10, the resulting EDC (dashed orange line) closely follows that of the target RIR (solid black line) until the two reach approximately -47 dB. Then, the two deviate before meeting again at -60 dB. Still, a direct comparison between EDCs in the range of -50 dB to -70 dB is not entirely reliable since the RIR has so little energy that background and sensor noise take on a much more relevant role when it comes to integrating the energy of the measured signal.

Overall, the proposed optimization method proves to perform well in fitting the RIR under scrutiny, with Table 4 reporting an error on all three reverberation time metrics of approximately 10 ms, ΔD_{50} of 0.016%, and Δt_s of 19 μ s. As in the previous test case, the only metric for which the proposed method shows a lower performance with respect to one of the baselines is T_{60} . As a matter of fact, the HRTC is the only baseline to be once again characterized by a lower ΔT_{60} , with a value of 6.9 ms.

5.8 Excluding the EDP Loss Term

In developing our method, we noticed that using only the EDC loss function leads to ill-behaved IRs. Namely, we found that, while closely matching the desired EDC, the IR of an FDN trained using only $\mathcal{L}_{\text{EDC}}$, i.e., $\lambda = 0$, tends to exhibit an unrealistic echo distribution compared to the RIRs of real-life environments. In this section, we compare the results of our differentiable FDN trained without EDP regularization loss with those presented in Section 5.6 obtained using the composite loss function in (6). For conciseness, we limit our analysis to the Hallway RIR (h270); results obtained with other RIRs are comparable to what is shown below.

When excluding the EDP loss term from (6), the NMSE between true and predicted EDCs (8) is slightly lower than that of the proposed method, i.e., 4.7×10^{-3} and 5.2×10^{-3} , respectively. Yet, the MSE between true and predicted EDPs (15) is 0.395, i.e., two orders of magnitude greater than the 0.0046 reported in Table 1 for the proposed method. This can be observed in Figure 13b, showing that the echo density when $\lambda = 0$ (dash-dotted purple line) is far from the desired profile (solid black line). The target RIR and the proposed method (dashed orange line) produce an EDP with values consistently around one, indicating dense reverberation. On the contrary, the FDN trained without Soft EDP regularization yields an EDP with small values, signaling an uneven echo density due to the presence of a few prominent reflections [38]. This observation is confirmed by the IR shown in Figure 13a that exhibits a few clearly noticeable taps peaking above a denser reverberation tail.

Excluding the EDP loss term means solving a minimization problem with no constraints discouraging the model to use just a small number of delay lines to capture the overall EDC behavior. Since FDNs extend a parallel comb-filter structure, we believe that the behavior observed in Figure 13a is related to the well-understood problem occurring when short delay lines are strongly excited, which, in turn, aggravates the comb-like behavior of the FDN, ultimately resulting in an unpleasing metallic sound quality [18, 41].

5.9 Soft EDP Approximation

Finally, we discuss the approximation capabilities of the proposed Soft EDP function introduced in Section 4.5.2. Figure 14 shows the non-differentiable EDP (solid black line) defined in (9) against several Soft EDP approximations of the three RIRs considered in the present study. We test various scaling parameters κ , namely 10^2 , 10^3 , and 10^4 , along with the proposed time-varying κ_n linearly increasing from 10^2 ($n = 0$) to 10^5 ($n = L_{T_{60}} - 1$). We depict the profiles only for time indices below the T_{60} , as this range is the one considered when training the FDNs.

In Figure 14, we may notice that $\kappa = 10^2$ yields a poor approximation of the reference EDP beyond the very first few ms. We also observe that $\kappa = 10^3$ and $\kappa = 10^4$ provide relative improvements. However, after some time, the approximation starts to degrade in a similar fashion as for $\kappa = 10^2$. Conversely, the proposed Soft EDP with time-varying scaling (dashed orange line) is able to closely match the non-differentiable reference profile all the way up to the T_{60} in Figure 14a, while gracefully combating gradient vanishing (see Section 4.5.2). Notably, however, Figure 14c shows that the approximation in the very last portion of the longest RIR considered, i.e., Gym (h052), significantly differs from the reference profile. To a lesser extent, this is also noticeable in Figure 14b. Nevertheless, it is worth mentioning that, around the estimated T_{60} , the energy of the RIR is already almost entirely vanished, and the EDP itself suffers from statistical uncertainty due to sensor and 16-bit quantization noise.

5.10 Limitations

In this work, we focused on two important perceptual characteristics of room impulse responses: energy decay and echo density. While rendering these acoustic features is essential for any artificial reverberation algorithm that aims to be realistic, by themselves, energy decay and echo density are not enough to comprehensively model all perceptual qualities of reverberation. In particular, matching the spectral envelope of the measured RIR turns out to play a crucial role in room acoustic simulation [39].

However, Figures 15, 16, 17 show that none of the FDNs considered in the present study manages to capture the frequency response of the target

Table 2 Metrics for the Gym RIR ($\lambda = 1$).

	T_{20}	ΔT_{20}	T_{30}	ΔT_{30}	T_{60}	ΔT_{60}
Target	0.8616	—	0.9161	—	1.2257	—
GA	0.6334	0.2282	0.6969	0.2193	0.8117	0.4139
HRTC	1.2592	0.3977	1.2526	0.3365	1.2189	<u>0.0068</u>
Colorless	0.8769	<u>0.0154</u>	1.3036	0.3875	1.3551	0.1294
Ours	0.7607	0.1009	0.9136	<u>0.0025</u>	1.1854	0.0403

	C_{80}	ΔC_{80}	D_{50}	ΔD_{50}	t_s	Δt_s
Target	12.1061	—	89.0091	—	22.8994	—
GA	11.9853	<u>0.1208</u>	91.1939	2.1849	19.3434	3.5560
HRTC	7.8383	4.2678	79.4541	9.5550	38.1226	15.2232
Colorless	10.1037	2.0024	80.4545	8.5546	27.8442	4.9449
Ours	11.8266	0.2795	88.2766	<u>0.7325</u>	22.9584	<u>0.0591</u>

Table 3 Metrics for the Hallway RIR ($\lambda = 0.1$).

	T_{20}	ΔT_{20}	T_{30}	ΔT_{30}	T_{60}	ΔT_{60}
Target	0.5289	—	0.6010	—	0.6067	—
GA	0.4200	0.1089	0.4233	0.1777	0.4329	0.1738
HRTC	0.6341	0.1052	0.6325	0.0315	0.6178	<u>0.0111</u>
Colorless	0.4350	0.0939	0.4596	0.1414	0.5730	0.0337
Ours	0.5031	<u>0.0259</u>	0.5716	<u>0.0294</u>	0.7023	0.0956


	C_{80}	ΔC_{80}	D_{50}	ΔD_{50}	t_s	Δt_s
Target	14.0797	—	90.6917	—	20.1163	—
GA	15.5019	1.4223	92.1064	1.4147	18.3649	1.7514
HRTC	11.4092	2.6705	88.2675	2.4242	20.8044	0.6881
Colorless	13.7608	0.3188	87.4117	3.2801	18.7276	1.3887
Ours	14.0713	<u>0.0083</u>	90.5123	<u>0.1794</u>	20.1487	<u>0.0324</u>

Table 4 Metrics for the Pizzeria RIR ($\lambda = 0.1$).


	T_{20}	ΔT_{20}	T_{30}	ΔT_{30}	T_{60}	ΔT_{60}
Target	0.1643	—	0.1794	—	0.2062	—
GA	0.1172	0.0471	0.1235	0.0559	0.1417	0.0645
HRTC	0.2252	0.0609	0.2151	0.0358	0.2131	<u>0.0069</u>
Colorless	0.2288	0.0645	0.2050	0.0256	0.1911	0.0151
Ours	0.1543	<u>0.0099</u>	0.1694	<u>0.0100</u>	0.2166	0.0104

	C_{80}	ΔC_{80}	D_{50}	ΔD_{50}	t_s	Δt_s
Target	30.9883	—	99.3819	—	7.1698	—
GA	40.6833	9.6950	99.7989	0.4170	6.4524	0.7174
HRTC	25.1428	5.8455	98.6346	0.7473	9.4239	2.2541
Colorless	23.9120	7.0763	97.8538	1.5281	10.0684	2.8986
Ours	32.1683	<u>1.1801</u>	99.3988	<u>0.0168</u>	7.1891	<u>0.0194</u>

RIRs. This, after all, is not among the objectives of the respective parameter selection/tuning algorithms, except for the GA baseline, whose fitness function amounts to a L^1 -loss between MFCCs. Still, despite considering cepstral features, the magnitude of the resulting transfer function is far from resembling the target spectrum.



(a)




(b)

Fig. 13 (a) IR and (b) EDP obtained by training the FDN without EDP regularization loss ($\lambda = 0$).


On the one hand, such a conspicuous mismatch entails that the output signals of the FDNs sound different not only from one another but also from the corresponding input signal convolved with the target RIR. On the other hand, to the best of our knowledge, there is no easy way to decouple spectral coloration from sound energy decay without affecting the latter.

In turn, this undermines the reliability of any perceptual test assigning similarity scores to each method with respect to the target, as subjective judgments would be significantly influenced by differing coloration. In this respect, pilot experiments proved inconclusive, highlighting the need for further investigation into spectro-temporal modeling.


In practice, it would be possible to extend the cost function to the frequency-dependent case by including an additional regression loss term in (6).



(a) Pizzeria (h214)



(b) Hallway (h270)



(c) Gym (h052)

Fig. 14 Non-differentiable EDP (Reference) compared with the proposed Soft EDP function for different values of the Sigmoid scaling parameter.

However, a thorough analysis of this approach lies beyond the scope of the present work and is left for future work.

6 Conclusions

We proposed a method for optimizing all the parameters of a time-invariant frequency-independent Feedback Delay Network (FDN) in order to match the reverberation of a given room




Fig. 15 Magnitude of the frequency response of the Gym RIR (h052) and corresponding FDN transfer functions.




Fig. 16 Magnitude of the frequency response of the Hallway RIR (h270) and corresponding FDN transfer functions.




Fig. 17 Magnitude of the frequency response of the Pizzeria RIR (h214) and corresponding FDN transfer functions.

through perceptually meaningful metrics. In the present work,

- i. we introduced a differentiable FDN with learnable delay lines,
- ii. we developed a novel optimization framework for *all* FDN parameters based on automatic differentiation,
- iii. we applied gradient-based optimization with the objective of matching selected acoustic features of measured RIRs,
- iv. we presented an innovative use of established perceptually-motivated acoustic measures as loss terms,
- v. we proposed a differentiable approximation of the well-known normalized echo density profile named Soft EDP.

In particular, we presented a new differentiable FDN that is characterized by learnable delay lines realized exploiting operations in the frequency domain. Thus, we jointly trained all FDN parameters via backpropagation taking into account a composite loss consisting of two terms: the normalized mean square error between target and predicted EDCs and the mean square error between target and predicted Soft EDPs. We tested the methodology on three RIRs of real rooms taken from a publicly available dataset, and we demonstrated that the Soft EDP term is essential for obtaining an IR that resembles a realistic RIR. Finally, we evaluated the methods against three baseline methods considering widespread metrics, including reverberation time, clarity, definition, and center time. Overall, the proposed approach was able to outperform the baselines across different metrics.

Future work includes the application of the proposed approach to frequency-dependent FDNs, which are able to account for a frequency-specific decay in time, or to multiple-input multiple-output (MIMO) delay networks.

Acknowledgments. Alessandro Ilic Mezza and Riccardo Giampiccolo wish to thank Xenofon Karakonstantis for the helpful discussion.

Declarations

- Availability of data and materials: The datasets generated and/or analyzed during the current study are available on the MIT

Acoustical Reverberation Scene Statistics Survey website, https://mcdermottlab.mit.edu/Reverb/IR_Survey.html.

- Funding: This work was partially supported by the European Union under the Italian National Recovery and Resilience Plan (NRRP) of NextGenerationEU, partnership on “Telecommunications of the Future” (PE000000001 — program “RESTART”), and received funding support as part of the JRC STEAM STM–Politecnico di Milano agreement and from the Engineering and Physical Sciences Research Council (EPSRC) under the “SCalable Room Acoustics Modelling (SCReAM)” Grant EP/V002554/1.
- Competing interests: The authors declare that they have no competing interests.
- Authors’ contributions: A. I. Mezza conceptualized the study, designed and implemented the proposed method, run the experiments, and drafted the manuscript. R. Giampiccolo contributed to the design of the proposed method, run the experiments, and drafted part of the manuscript. E. De Sena contributed to the method and codebase, and drafted part of the manuscript. A. Bernardini revised the manuscript and supervised the work.

References

- [1] Apostolopoulos, J.G., Chou, P.A., Culbertson, B., Kalker, T., Trott, M.D., Wee, S.: The road to immersive communication. *Proc. of the IEEE* **100**(4), 974–990 (2012)
- [2] Potter, T., Cvetković, Z., De Sena, E.: On the relative importance of visual and spatial audio rendering on VR immersion. *Front. Signal Process.* **2** (2022)
- [3] Geronazzo, M., Tissieres, J.Y., Serafin, S.: A minimal personalization of dynamic binaural synthesis with mixed structural modeling and scattering delay networks. In: *Proc. IEEE Int. Conf. Acoust. Speech Signal Process.*, pp. 411–415 (2020)
- [4] Välimäki, V., Parker, J.D., Savioja, L., Smith, J.O., Abel, J.S.: Fifty years of artificial reverberation. *IEEE Trans. Audio Speech Lang. Process.* **20**(5), 1421–1448 (2012)
- [5] Wefers, F.: *Partitioned Convolution Algorithms for Real-time Auralization* vol. 20. Logos Verlag Berlin GmbH, Berlin, Germany (2015)
- [6] Schroeder, M.R.: Natural sounding artificial reverberation. *J. Audio Eng. Soc.* **10**(3), 219–223 (1961)
- [7] Jot, J.-M., Chaigne, A.: Digital delay networks for designing artificial reverberators. In: *90th Audio Eng. Soc. Convention* (1991)
- [8] Schlecht, S.J., Habets, E.A.P.: On lossless feedback delay networks. *IEEE Trans. Sig. Process.* **65**(6), 1554–1564 (2016)
- [9] Bai, H., Richard, G., Daudet, L.: Late reverberation synthesis: From radiance transfer to feedback delay networks. *IEEE Trans. Audio Speech Lang. Process.* **23**(12), 2260–2271 (2015) <https://doi.org/10.1109/TASLP.2015.2478116>
- [10] De Sena, E., Hacıhabiboğlu, H., Cvetković, Z., Smith, J.O.: Efficient synthesis of room acoustics via scattering delay networks. *IEEE/ACM Trans. Audio Speech Lang. Process.* **23**(9), 1478–1492 (2015)
- [11] Stevens, F., Murphy, D.T., Savioja, L., Välimäki, V.: Modeling sparsely reflecting outdoor acoustic scenes using the waveguide web. *IEEE/ACM Trans. Audio Speech Lang. Process.* **25**(8), 1566–1578 (2017)
- [12] Bona, R., Fantini, D., Presti, G., Tiraboschi, M., Engel Alonso-Martinez, J.I., Avanzini, F.: Automatic parameters tuning of late reverberation algorithms for audio augmented reality. In: *Proc. 17th Int. Audio Mostly Conf.*, pp. 36–43 (2022). <https://doi.org/10.1145/3561212.3561236>
- [13] Chemistruck, M., Marcolini, K., Pirkle, W.: Generating matrix coefficients for feedback delay networks using genetic algorithm. In: *133rd Audio Eng. Soc. Convention* (2012)
- [14] Shen, J., Duraiswami, R.: Data-driven feedback delay network construction for real-time virtual room acoustics. In: *Proc. 15th Int.*

- Audio Mostly Conf., pp. 46–52 (2020)
- [15] Coggin, J., Pirkle, W.: Automatic design of feedback delay network reverb parameters for impulse response matching. In: 141st Audio Eng. Soc. Convention (2016)
 - [16] Ibnyahya, I., Reiss, J.D.: A method for matching room impulse responses with feedback delay networks. In: 153rd Audio Eng. Soc. Convention (2022)
 - [17] Lee, S., Choi, H.-S., Lee, K.: Differentiable artificial reverberation. *IEEE/ACM Trans. Audio Speech Lang. Process.* **30**, 2541–2556 (2022) <https://doi.org/10.1109/TASLP.2022.3193298>
 - [18] Dal Santo, G., Prawda, K., Schlecht, S., Välimäki, V.: Differentiable feedback delay network for colorless reverberation. In: *Proc. 26th Int. Conf. Digital Audio Effects*, pp. 244–251 (2023)
 - [19] Mezza, A.I., Giampiccolo, R., Bernardini, A.: Data-driven parameter estimation of lumped-element models via automatic differentiation. *IEEE Access* **11**, 143601–143615 (2023) <https://doi.org/10.1109/ACCESS.2023.3339890>
 - [20] Baydin, A.G., Pearlmutter, B.A., Radul, A.A., Siskind, J.M.: Automatic differentiation in machine learning: a survey. *J. Mach. Learning Res.* **18**, 1–43 (2018)
 - [21] Abel, J.S., Huang, P.: A simple, robust measure of reverberation echo density. In: 121st Audio Eng. Soc. Convention (2006). Audio Engineering Society
 - [22] Rocchesso, D., Smith, J.O.: Circulant and elliptic feedback delay networks for artificial reverberation. *IEEE Trans. Speech Audio Process.* **5**(1), 51–63 (1997) <https://doi.org/10.1109/89.554269>
 - [23] Schlecht, S.J., Habets, E.A.P.: Feedback delay networks: Echo density and mixing time. *IEEE/ACM Trans. Audio Speech Lang. Process.* **25**(2), 374–383 (2016)
 - [24] Schlecht, S.J., Habets, E.A.P.: Time-varying feedback matrices in feedback delay networks and their application in artificial reverberation. *J. Acoust. Soc. Am.* **138**(3), 1389–1398 (2015)
 - [25] Oppenheim, A.V., Schafer, R.W., Buck, J.R.: *Discrete-time Signal Processing*, 2nd edition edn. Prentice Hall, ??? (1999)
 - [26] Heise, S., Hlatky, M., Loviscach, J.: Automatic adjustment of off-the-shelf reverberation effects. In: 126th Audio Eng. Soc. Convention (2009)
 - [27] Fogel, L.J.: *Intelligence Through Simulated Evolution: Forty Years of Evolutionary Programming*. John Wiley & Sons, Inc., Hoboken, NJ, USA (1999)
 - [28] Nelder, J.A., Mead, R.: A simplex method for function minimization. *Comput. J.* **7**(4), 308–313 (1965)
 - [29] Kennedy, J., Eberhart, R.: Particle swarm optimization. In: *Proc. Int. Conf. Neural Netw.*, vol. 4, pp. 1942–1948 (1995)
 - [30] Črepinšek, M., Liu, S.-H., Mernik, M.: Exploration and exploitation in evolutionary algorithms: A survey. *ACM Comput. Surv.* **45**(3), 1–33 (2013)
 - [31] Engel, J., Hantrakul, L.H., Gu, C., Roberts, A.: DDSP: Differentiable digital signal processing. In: *Int. Conf. Learning Representations* (2020)
 - [32] Esqueda, F., Kuznetsov, B., Parker, J.D.: Differentiable white-box virtual analog modeling. In: *Proc. 23rd Int. Conf. Digital Audio Effects*, pp. 41–48 (2021)
 - [33] Shintani, M., Ueda, A., Sato, T.: Accelerating parameter extraction of power mosfet models using automatic differentiation. *IEEE Trans. Power Electron.* **37**(3), 2970–2982 (2022) <https://doi.org/10.1109/TPEL.2021.3118057>
 - [34] Schlecht, S.J., Habets, E.A.P.: On lossless feedback delay networks. *IEEE Trans. Signal*

- Process. **65**(6), 1554–1564 (2016)
- [35] Lezcano-Casado, M., Martinez-Rubio, D.: Cheap orthogonal constraints in neural networks: A simple parametrization of the orthogonal and unitary group. In: Int. Conf. Mach. Learning, pp. 3794–3803 (2019)
 - [36] Schroeder, M.R.: New method of measuring reverberation time. *J. Acoust. Soc. Am.* **37**(6), 1187–1188 (1965)
 - [37] Howard, D., Angus, J.: *Acoustics and Psychoacoustics*. Routledge, London, UK (2013)
 - [38] Huang, P., Abel, J.S.: Aspects of reverberation echo density. In: 123rd Audio Eng. Soc. Convention (2007)
 - [39] Traer, J., McDermott, J.H.: Statistics of natural reverberation enable perceptual separation of sound and space. *Proc. Natl. Acad. Sci.* **113**(48), 7856–7865 (2016) <https://doi.org/10.1073/pnas.1612524113>
 - [40] Schlecht, S.J.: FDNTB: The feedback delay network toolbox. In: Proc. Int. Conf. Digital Audio Effects, pp. 211–218 (2020)
 - [41] Schroeder, M.R., Logan, B.F.: “colorless” artificial reverberation. *IRE Transactions on Audio* **AU-9**(6), 209–214 (1961) <https://doi.org/10.1109/TAU.1961.1166351>
 - [42] Kingma, D., Ba, J.: Adam: A method for stochastic optimization. In: Int. Conf. Learning Representations (2015)
 - [43] Goldberg, D.E.: *Genetic Algorithms in Search, Optimization, and Machine Learning*. Addison-Wesley, Boston, MA, USA (1989)
 - [44] Schlecht, S.J., Habets, E.A.P.: Accurate reverberation time control in feedback delay networks. *Proc. Int. Conf. Digital Audio Effects*, 337–344 (2017)
 - [45] Välimäki, V., Liski, J.: Accurate cascade graphic equalizer. *IEEE Signal Process. Lett.* **24**(2), 176–180 (2016)
 - [46] Välimäki, V., Reiss, J.D.: All about audio equalization: Solutions and frontiers. *Appl. Sci.* **6**(5) (2016) <https://doi.org/10.3390/app6050129>
 - [47] Edelman, A., Rao, N.R.: Random matrix theory. *Acta Numerica* **14**, 233–297 (2005) <https://doi.org/10.1017/S0962492904000236>
 - [48] Acoustics – Measurement of room acoustic parameters. Part 1: Performance spaces. ISO 3382-1:2009, International Organization for Standardization, Geneva, Switzerland, June 2009